1/11/2018 Product Details



Product 20313

Number:

Order CF9DS/E/827

Abbreviation:

General DULUX 9W single compact fluorescent lamp with 4-pin base, 2700K color temperature, 82 CRI, for use with electronic

Description: and dimming ballasts

Product Information

Abbrev. With Packaging Info. CF9DSE827 50/CS 1/SKU Average Rated Life (hr) 20000 Base 2G7 Bulb S (T4) 80 - 89 Color Rendering Index (CRI) Color Temperature/CCT (K) 2700 Diameter (in) 0.000 0.00 Diameter (mm) Family Brand Name Dulux® S/E **Industry Standards** IEC 60901-2009 Initial Lumens at 25C 600 499 Mean Lumens at 25C 5.7 Maximum Overall Length - MOL (in) Maximum Overall Length - MOL (mm) 145 Nominal Wattage (W) 9.00



Footnotes

- Approximate initial lumens after 100 hours operation.
- Minimum starting temperature is a function of the ballast; consult the ballast manufacturer.
- There is a NEMA supported, industry issue where T2, T4, and T5 fluorescent and compact fluorescent lamps operated on high frequency ballasts may experience an abnormal end-of-life phenomenon. This end-of-life phenomenon can resultin one or both of the following: 1. Bulb wall cracking near the lamp base. 2. The lamp can overheat in the base area and possibly melt the base and socket. NEMA recommends that high frequency compact fluorescent ballasts have an end-of-life shutdown circuit which will safely and reliably shut down the system in the rare event of an abnormal end-of-life failure mode described above. The final requirements of this system are yet to be defined by ANSI. For additional information refer to NEMA papers on their WEBSITE at www.NEMA.org.
- The life ratings of fluorescent lamps are based on 3 hr. operating cycles under specified conditions and with ballast meeting ANSI specifications. If operating cycle is increased, there will be a corresponding increase in the average hours life.
- Rule of Thumb for Compact Fluorescent Lamps: Divide wattage of incandescent lamp by 4 to determine approximate wattage of compact fluorescent lamp that will provide similar light output.