

## U9647N-RL-200-KK





Catalog Number	U9647N-RL-200-KK
Marketing Product Description	4 Terminal Ringless Small Hub Open Horn Bypass 1-200 Ampere Main Breaker
UPC	784572322486
Length (IN)	4.844
Width (IN)	13
Height (IN)	33
Brand Name	Milbank
Туре	Ringless Meter Socket
Application	Meter Socket With Main
Standard	UL Listed;Type 3R
Voltage Rating	Up to 240 Volts Alternating Current
Amperage Rating	200 Continuous Ampere
Phase	1 Phase
Frequency Rating	60 Hertz
Size	4.844L x 13W x 33H
Number Of Cutouts	1
Cutout Size	One 200 Ampere Main Breaker
Cable Entry	Overhead or Underground
Terminal	Lay in
Insulation	Glass Polyester

Mounting	Surface Mount
Enclosure	G90 Galvanized Steel with Powder Coat Finish
Jaw Quantity	4 Terminal
Bypass Type	Horn Bypass
Number of Meter Positions	1 Position
Equipment Ground	2 Barrel Ground Lug
Hub Opening	Small Hub Opening
Line Side Wire Range	6 AWG - 350 kcmil
Load Side Wire Range	Three 6 AWG - 350 kcmil
Number Of Receptacles	0


Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.

	-				
<b>A</b>	٨	<b>(</b>	6	٠	
	•		<u>ديد</u>	8	
33"					
					D
<u> </u>	0			<b>©</b>	
		– 13" C	D.D. —	_	





FEATURE TABLE		
ITEM	QTY	DESCRIPTION
Α	8	U/L MNTG.EMBOSS
В	1	1/4 SOLID K.O.
С	1	1/4, 1/2 CONC. K.O.
D	3	11/4, 11/2, 2, 21/2 CONC. K.O.
Е	3	11/4, 11/2, 2, 21/2, 3 CONC. K.O.





All dimensions are +/- 1/16". Drawing views are not to scale.

Version:

1

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.