

Multi-Gang Switch Boxes

1-5/8" Deep

Features

- 1-5/8" deep
- Welded
- Available with 1/2" and 3/4" Concentric KO's
- Available in 2 thru 8 gangs

Applications

- Used when more than two devices or outlets are required in one box
- Multi-Gang Switch boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices
- Use to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions




E195124




Standard Material


- Galvanized steel




MSB12
Concentric KO




MSB13
Concentric KO




MSB14
Concentric KO



MSB15
Concentric KO



MSB16
Concentric KO



MSB18
Concentric KO

Catalog Number	UPC	Description	Knockouts		Cubic Inches	Ship Case	Weight/Case
			Sides	Bottom			
MSB12	01952	1-5/8" deep, 2 gang	(12) - 1/2" & 3/4" CON	(4) - 1/2" & (2) - 3/4"	46	25	33
MSB13	01953	1-5/8" deep, 3 gang	(14) - 1/2" & 3/4" CON	(6) - 1/2" & (4) - 3/4"	58.5	20	29
MSB14	01955	1-5/8" deep, 4 gang	(16) - 1/2" & 3/4" CON	(6) - 1/2" & (4) - 3/4"	71	20	36
MSB15	01958	1-5/8" deep, 5 gang	(18) - 1/2" & 3/4" CON	(6) - 1/2" & (4) - 3/4"	81	10	20
MSB16	01960	1-5/8" deep, 6 gang	(20) - 1/2" & 3/4" CON	(6) - 1/2" & (4) - 3/4"	95	5	12
MSB18	01961	1-5/8" deep, 8 gang	(24) - 1/2" & 3/4" CON	(6) - 1/2" & (4) - 3/4"	122	5	15